

AVTECH ELECTROSYSTEMS LTD.

**NANOSECOND WAVEFORM ELECTRONICS
ENGINEERING . MANUFACTURING**

□ **P.O. BOX 265
OGDENSBURG
NEW YORK
13669
(315) 472-5270**

✠ **BOX 5120 STN. "F"
OTTAWA, ONTARIO
CANADA K2C 3H4
(613) 226-5772
TELEX 053-4591**

INSTRUCTIONS

MODEL AVO-5C-C-N PULSE GENERATOR


S.N. :

WARRANTY

Avtech Electrosystems Ltd. warrants products of its manufacture to be free from defects in material and workmanship under conditions of normal use. If, within one year after delivery to the original owner, and after prepaid return by the original owner, this Avtech product is found to be defective, Avtech shall at its option repair or replace said defective item. This warranty does not apply to units which have been disassembled, modified or subjected to conditions exceeding the applicable specifications or ratings. This warranty is the extent of the obligation or liability assumed by Avtech with respect to this product and no other warranty or guarantee is either expressed or implied.


Fig. 1

PULSE GENERATOR TEST ARRANGEMENT




Notes:

- 1) The equipment should be connected in the general fashion shown above. Since the AVO unit provides an output pulse rise time as low as 5 nsec a fast oscilloscope (at least 50 MHz and preferably 200 MHz) should be used to display the waveform. If a sampling scope is used, a 50 db (or greater) attenuator should be used to insure a peak input to the scope of less than 0.5 volts.
- 2) The sync output channel provides a +0.5 volt 100 nsec pulse.
- 3) To obtain a stable output display the PRF controls on the front panel should be set mid-range. The front panel TRIG toggle switch should be in the INT position. The front panel DELAY control and the scope triggering controls are then adjusted to obtain a stable output. The scope may then be used to set the desired PRF by rotating the PRF controls. The main output is delayed with respect to the SYNC output by about 0 to 200 nsec depending on the DELAY control setting.
- 4) The AVO-5C-T4 transformer module transforms the 50 volt output of the AVO-5C mainframe to 25 volts to 6.0 ohm to provide a peak diode as high as 4 amperes. (Use AVO-5C-TB to obtain 8 amperes as discussed in paragraph 5). The AVO-5C-T4 module connects to the mainframe via two parallel 50 ohm miniature coaxial cables approx. 2 feet in length. The output terminals of the transformer module consists of a short length of microstrip transmission line protruding from the module chassis. The OUT terminal is the center conductor which is bounded on both sides by the ground plane (see below):



The diode load and series resistor (5.0 to 7.0 ohm 1/2 W carbon composition resistor) should be connected between the OUT and GND terminals using very short leads (≤ 0.2 cm). The voltage across the resistor-diode load may be monitored by connecting a length of 80 mil semi-rigid 50 ohm cable as shown below:




Take care to insure that during soldering the OUT conductor is not shorted to the chassis. Also, use minimal heat when soldering.

- 5) The AVO-5C-T8 module is used to obtain peak output currents as high as 8 amperes. This module transforms the 50 volt output of the AVO-5C mainframe to 12 volts to 1.5 ohms. The connections to the module are as per the AVO-5C-T4 module but the resistor should be about 1.5 ohm.
- 6) **CAUTION:** At maximum PRF and maximum pulse width, the AVO-5C unit provides an average output power as high as 20 watts. Considerable care must be taken to insure that the resistive load and the diode can dissipate this extremely high power. The power dissipated can be reduced by reducing the PRF and the pulse width.

- 7) To voltage control the output pulse width, remove the jumper wire between banana plugs A and B on the back panel and apply 0 to +10V to connector B ($R_{IN} \geq 10K$). (option).
- 8) To voltage control the output amplitude, remove the jumper wire between banana plugs A and B on the back panel and apply 0 to +10V to connector B ($R_{IN} \geq 10K$). (option).
- 9) To offset the output pulse apply the desired offset volt (0 to ± 50 volts) to the OS terminal on the side of the AVD-5C-T module. This voltage will appear directly at the output terminals. CAUTION: The maximum offset current should not exceed 250 mA.

Fig. 2

FRONT PANEL CONTROLS



- (1) ON-OFF Switch. Applies basic prime power to all stages.
- (2) PRF Control. Varies PRF from about 50 Hz to 5 MHz. The
- (3) operating PRF should be set using a scope.

	PRF MIN	PRF MAX
RANGE 1	1.6 KHz	8 KHz
RANGE 2	8 KHz	40 KHz
RANGE 3	40 KHz	200 KHz
RANGE 4	200 KHz	1.0 MHz
RANGE 5	1.0 MHz	5.0 MHz


CAUTION: At maximum PRF and maximum pulse width, the AVO-5C unit provides an average output power as high as 20 watts. Considerable care must be taken to insure that the resistive load and the diode can dissipate this extremely high power. The power dissipated can be reduced by reducing the PRF and the pulse width.

- (4) DELAY Control. Controls the relative delay between the reference output pulse provided at the SYNC output (5) and the main output (8). This delay is variable over the range of about 0 to 200 nsec.
- (5) SYNC Output. This output precedes the main output (8) and is used to trigger the sampling scope time base. The output is a TTL level 100 nsec (approx) pulse capable of driving a fifty ohm load.
- (6) PW Control. A one turn control which varies the output pulse width from 5 to 50 nsec. CAUTION: At maximum PRF and maximum pulse width, the AVO-5C unit provides an average output power as high as 20 watts. Considerable care must be taken to insure that the resistive load and the diode can dissipate this extremely high power. The power dissipated can be reduced by reducing the PRF and the pulse width.
- (7) AMP Control. The output pulse amplitude is controlled by means of the one turn potentiometer (AMP).
- (8) OUT Connectors. Two SMA connectors for two miniature coaxial cables connected to the AVO-5C-T module.
- (9) EXT-INT Control. With this toggle switch in the INT position, the PRF of the AVO unit is controlled via an internal clock which in turn is controlled by the PRF controls. With the toggle switch in the EXT position, the AVO unit requires a 20 nsec TTL level pulse applied at the TRIG input in order to trigger the output stages. In addition, in this mode, the scope time base must be triggered by the external trigger source.

- (10) TRIG Input. The external trigger signal is applied at this input when the EXT-INT toggle switch is in the EXT position. The output pulse at (8) appears about 30 nsec after the application of the TRIG pulse.

Fig. 3

BACK PANEL CONTROLS



(1) FUSED CONNECTOR, VOLTAGE SELECTOR. The detachable power cord is connected at this point. In addition, the removable cord is adjusted to select the desired input operating voltage. The unit also contains the main power fuse.

(2) MONITOR Output (M). Output voltage (to fifty ohms) at this point (V_M) can be related to AVO-5A-T output current (I_{OUT}) as follows (option):

$$I_{OUT} = 1.6 V_M \quad (\text{Volts and Amps})$$


(3) To voltage control the output pulse width, remove the jumper wire between banana plugs A and B and apply 0 to +10V to connector B ($R_{TN} \geq 10K$). (option).

(4) To voltage control the output amplitude, remove the jumper wire between banana plugs A and B and apply 0 to +10V to connector B ($R_{TN} \geq 10K$). (option).


Fig. 4

SYSTEM BLOCK DIAGRAM

POWER SUPPLIES




To Fig. 5



To Pin 3
AVO-5C-AMP-PS,
Fig. 5

Fig. 5

SYSTEM BLOCK DIAGRAM



SYSTEM DESCRIPTION AND REPAIR PROCEDURE

The AVO-5C-N-C unit consists of the following basic modules:

- 1) AVO-5C-N-PG pulse generator module
- 2) AVO-5C-CL clock module
- 3) +24V power supply board
- 4) -75V power supply board
- 5) AVO-5C-AMP-PS amplitude controller

The modules are interconnected as shown in Fig. 4 and Fig. 5.

In the event of an instrument malfunction, it is most likely that some of the output switching elements (SLBT) may have failed due to an output short circuit condition or to a high duty cycle condition. The switching elements may be accessed by removing the cover plate on the bottom side of the instrument. The cover plate is removed by removing the two 2-56 Phillips screws. NOTE: First turn off the prime power. CAUTION: Briefly ground the SLBT tabs to discharge the -70 volts power supply potential. The elements may be removed from their sockets by means of a needle nosed pliers after removing the four counter sunk 2-56 Phillips screws which attach the small aluminum heat sinks to the body of the AVO-5C-PG module. The SLBT is a selected VMOS power transistor in a TO 220 packages and may be checked on a curve tracer. If defective, replacement units should be ordered directly from Avtech. When replacing the SLBT switching elements, take care to insure that the short lead (of the three leads) is adjacent to the black dot on the chassis. The SLBT elements are electrically isolated from the small aluminum heat sinks but are bonded to the heat sinks using WAKEFIELD TYPE 155 HEAT SINK ADHESIVE. If the switching elements are not defective, then the four Phillips screws on the back panel should be removed. The top cover may then be slid off and the operation of the clock and power supply modules checked. The clock module is functioning properly if:

- a) 0.1 usec TTL level outputs are observed at pins 2 and 3.
- b) The PRF of the outputs can be varied over the range of 2 KHz to 5 Hz using the PRF controls.
- c) The relative delay between the pin 2 and 3 outputs can be varied by at least 0.1 usec by the DELAY control.

The sealed clock module must be returned to Avtech for repair or replacement if the above conditions are not observed.

Schroff 09.19.86 (Edition B)

-EW

-EA

-OS

-M