

INSTRUCTIONS

MODEL AV-141D AMPLIFIER

S.N.:

WARRANTY

Avtech Electrosystems Ltd. warrants products of its manufacture to be free from defects in material and workmanship under conditions of normal use. If, within one year after delivery to the original owner, and after prepaid return by the original owner, this Avtech product is found to be defective, Avtech shall at its option repair or replace said defective item. This warranty does not apply to units which have been disassembled, modified or subjected to conditions exceeding the applicable specifications or ratings. This warranty is the extent of the obligation or liability assumed by Avtech with respect to this product and no other warranty or guarantee is either expressed or implied.

GENERAL OPERATING INSTRUCTIONS

The Model AV-141D-APLA amplifier is designed to amplify bipolar nanosecond rise time baseband pulses in the pulse width range of about 5.0 ns and higher and CW signals in the frequency range of DC to 75 MHz. The basic specifications for the unit are as follows:

| | |
|----------------------|--|
| Gain: | x 50 (Voltage, non-inverting) |
| Peak output voltage: | ± 3 Volt |
| Rise time: | < 5.0 ns |
| Impedance level: | 50 Ohms nominal |
| Bandwidth: | DC to 75 MHz |
| Max. noise figure: | 3.2 nV / Hz |
| Prime power: | +15 Volts, 50 mA max -15 Volts, 50 mA max |
| Connectors: | SMA |
| Size: | 1.4 x 1.1 x 2.3 inches |

The DC offset on the output may be set to zero by making minor adjustments to the OS trim pot on the "OUT" end of the chassis.

CAUTION: The unit may be damaged if the DC voltage power supply voltage exceeds ±18.0 Volts or if the power supply voltages are reversed. The 1N4746A zener diodes are installed across the ±15 VDC input terminals to protect the unit against these factors. Note that the

input power supply voltages may be as low as ± 7 Volts.

CAUTION: The input to this amplifier does not include any overload protection and so it may be damaged if subjected to high amplitude spurious outputs such as those provided by some PMT. The warranty does not apply to such failures.